

distyNotruf There when you need it.

Emergency Button

for cordless phones, router and all DECT systems

Install once

FI

up to 15 months of standby time



www.disty.de





distyNotruf stationär is used to connect directly to persons in a position of trust – at the touch of a button

- Easy installation
- Easy operation
- Speakerphone feature

distyNotruf stationär can be of great help in emergencies or threatening situations.

You only need to specify in advance who to call for help. It can store up to 5 telephone numbers.* After pressing the distress call button, these numbers are called until help responds.

Scope of delivery

- distyNotruf stationär
- 2 batteries AAA
- Operating instructions
- USB cable

For a versatile

- **usage**, e.g.
- in case of illness
- call to security guards
 - staff call
 - etc.

CE

Mat.-No.: 5000390 EAN 4260047840328

All rights to change reserved.



Technical data

- DECT/GAP, EN 300 444 (Frequency range and transmission power: compliant with standards of EU/EFTA/AUS)
- Compatible with all consumer DECT/GAP base stations and all professional DECT systems
- Compatible with FRITZ!Box and Speedport Neo

There when you need it.

- Button for distress calls and operation
- LED Power indicator (in two colours)
- Microphone and speaker
- Operating voltage two batteries, AAA
- Standby time: >1 year
- Speaking time: >4 hours
- Interface for programming USB cable, Type A — USB, Type C
- System requirements: Windows 7/8/10
- Operating/storage temperature: -10°C to +60°C
- Weight approx. 52 g (incl. batteries)
- Plastic housing, 57 mm x 56 mm x 25 mm, Colour: anthrazite
- Protection class: IP 53
- Fixing with two screws

The first call number can be saved using the CLIP function. The remaining four memory locations can be "filled" via "ProgrammerApp" (Windows 7/8/10) additionally downloadable from www.disty.de.

> Help & Contact distynotruf@disty.de

disty communications GmbH

Andreas-Gayk-Straße 7–11 · D-24103 Kiel phone +49 (0)4 31 · 3 64 58 01

www.disty.de